

LogiLink_®

Solar Charging Power Bank 6000 mAh, with LED Flashlight

Art. No.: PA0290











Get Power When You're in a Traffic Jam

Solar charging function for emergency use or as an auxiliary power source.





Multiple Protections

Safe and reliable with overcurrent, overvoltage, overtemperature and short circuit protections.

Handy Emergency Flashlight

Built in LED flashlight with 3 modes: Steady, SOS and Strobe. SOS mode can be used as an emergency light in the dark or to light up an entire room.

Specification:

Capacity	6000 mAh 3.7 V Li-polymer battery
Input	USB-C: 5 V/2 A (10 W) Solar panel: 5 V/0.12 A (0.6 W) Maximum input: 10 W
Output	USB-A1: 5 V/2 A (10 W max.) USB-A2: 5 V/2 A (10 W max.) Maximum output: 10 W
LED Indicator	Green LED for solar charging; Blue LED for charging device and battery status
Protections	Over-charge, over-discharge, overload, over-current, over-voltage, over temperature and short circuit
Flashlight Modes	Steady, SOS and Strobe
Waterproof Grade	IP44
Housing Material	ABS
Color	Black and orange
Operating Temperature	0–45°C
Operating Humidity	40–60% RH (no condensation)
Dimensions	13.9 x 7.7 x 2.4 mm
Weight	199 g
Cable Length	30 cm

Package Contents:

- » 1 x Power Bank
- » 1 x USB-A to USB-C Charging Cable
- » 1 x User Manual

Package Information:

» Packing Dimension: 175 x 90 x 25 mm

» Packing Weight: 0.25 kg

» Carton Dimension: 380 x 270 x 190 mm

» Carton Q'ty: 40 pcs» Carton Weight: 10.39 kg





