

LogiLink®

Universal Power Adapter 3–12 V

With 7 Changeable Tips

Art. No.: PA0161A




Ideal as a replacement or secondary power adapter for electronics and small home appliance.

Features:

- » Reliable replacement or secondary power adapter in home or office
- » 6 selectable voltage levels (3/4.5/5/6/9/12 V) with 7 interchangeable tips
- » Adjust the voltage right on the plug with no tools required
- » Built-in over-current, over-voltage, over-temperature and short circuit protection ensures safe, stable power



Home/Office



For digital camera, battery chargers, mobile phone, router, games console and many others.



Voltage Switch

Specification:

Input Voltage	100–240 Vac 50/60 Hz 0.6 A max.
Output Power	3 V/2 A (6 W), 4.5 V/2 A (9 W), 5 V/2 A (10 W), 6 V/2 A (12 W), 9 V/2 A (18 W), 12 V/2 A (24 W max.)
Efficiency	VI
Operating Temperature	-10–35°C
Operating Humidity	35–85% RH (no condensation)
DC Plug	5.5 x 2.1 mm
Dimensions	8 x 8.7 x 3.2 cm (with plug, without cable)
Weight	146 g (include tips)
Cable Length	1.5 m
Color	Black



C	5.5 x 2.5 mm
L	3.0 x 1.1 mm
J	3.5 x 1.35 mm
I	2.5 x 0.7 mm
G	4.0 x 1.7 mm
H	3.5 mm jack
S	Micro USB



PA0161A



4 052792 080582

Made in China



*The specifications and pictures are subject to change without prior notice.
*All trade names referenced are the registered trademarks of their respective owners.



Package Contents:

- » 1 x Universal Power Adapter
- » 7 x Changeable Tips
- » 1 x User Manual

Package Information:

- » Packing Dimension: 127.5 x 35 x 176 mm
- » Packing Weight: 0.19 kg
- » Carton Dimension: 370 x 370 x 275 mm
- » Carton Q'ty: 40 pcs
- » Carton Weight: 7.9 kg



Warning

- *For use with Information Technology Equipment.
- *Compare the specifications of your device with the specifications of the adapter. The power current (A) of your device should be equal to or lower than the power current of the power supply.
- *Only to be used indoor.
- *Only to be used after powering on.
- *Only to be used within max load.
- *Remove the power adapter from its power source after use.



*The specifications and pictures are subject to change without prior notice.
*All trade names referenced are the registered trademarks of their respective owners.



PA0161A



4 052792 080582

Made in China