

LogiLink

2-Port USB-C Wall Outlet 1x CEE 7/3 Socket + 2x USB-C Ports

Art. No.: PA0331

Charge 2 USB-C devices simultaneously without power adapters while using the normal plug! Perfect for hotel rooms, restaurant, home and office.

Features:

- » Supply power for smartphones, digital products, or other electrical equipment
- » Charging 2 USB-C devices and 1 appliance at the same time
- » Standard German socket 80 x 80 mm
- » With safety shutter

Specification:



| Rated Power | 230 V~ 50 Hz, 16 A, 3600 W max. |
|--------------------------|---|
| USB Outputs | USB-C1/C2: 5 V/3 A (15 W), 9 V/2.77 A (25 W), 12 V/2.08 A (25 W max.) USB-C1+C2: 5 V/3 A (15 W max.) Total output: 25 W max. |
| PD Standard | PD 3.0 |
| Degree of Protection | IP20 |
| Color | White |
| Dimensions with Frame | 80 x 80 mm |
| Dimensions without Frame | 55 x 55 mm |
| Installation Depth | 29.5 mm |

Installation:

- 1. Connect the wires and install the receptacle into the wall.
- 2. Install the panel and screw the socket onto the receptacle.








Made in China

Circuit Drawing:





Package Contents:

» 1 x 2-Port USB-C Wall Outlet

» 1 x User Manual

Package Information:

- » Packing Dimension: 82 x 85 x 45 mm
- » Packing Weight: 0.107 kg
- » Carton Dimension: 490 x 380 x 280 mm
- » Carton Q'ty: 100 pcs
- » Carton Weight: 14 kg

Warning

ECE

- *Indoor use only.
- *Use in dry places.
- *The installation and assembly of electrical equipment may only be carried out by a qualified electrician!



